



Terminal

Plug-screw terminal 8pin
max. 2,5 qmm

Pin 2 and pin 5 are jumpered

1: +output 1, LRA/EVG input
2: -output 1-2
3: +output 2, LRA/EVG input

1-2: with emergency function
3-2: without emergency funct.

4: input 1, + 0-10V
5: input 1, - " (GND)
from SPS analog output

7-8: input 2, 230V AC line
without line, the lighting
connected to pin 1-2 is
switch 100% on, override
the SPS input pin 4-5.

Technical Data

Input 1, pin 4-5	0-10V DC
Input current	max. 1 mA
Input resistance	10 k Ohm
Output, pin 1-2, pin 2-3	current drain
Output current	max. 80mA, (1-10V) PNP transistor
Input 2, pin 7-8	230V AC
Input current	max. 5mA
Emergency lighting	
Precision	1 %
Insulation input 2	4 kV
Operating temperature	-10 - +50°C
Storage temperature	-30 - +80°C
Construction	PCB mount. TS35, EN50022
Weight	70 g
Dimensions	24 x 72 x 94 mm (WxHxD)

No Power supply converter for the adaptation of SPS analog output to EVG electronic lighting control systems.

Input analog 0-10V from SPS / DDC. Output current drain, replace a potentiometer.

If there is no line input pin7-8, the lighting which is connected to output 1 (pin1-2) is **on** = emergency function.

The output 2 (pin3-2) has no emergency function. If there is no SPS signal (input <1V), the light will switch off.

RINCK ELECTRONIC GMBH

Kleekamp 6
27356 Rotenburg Wümme
www.rinck-electronic.de
info@rinck-electronic.de

CONVERTER NP-SPS10V.EVG/N

Input 1	0 – 10 V DC
Input 2	230V AC, line
Output 1	1-10V current drain for EVG, with emergency function
Output 2	1-10V current drain for EVG, without emergency function

B 112

E_NP-SPS

01.07.04